



IAR/IUR/IER/CUR/CER SERIES

“1U, 1RU” HYDRAULIC MAGNETIC CIRCUIT PROTECTORS

Introduction

The Airpax™ IAR/IUR/IER/CUR/CER series is a snap-acting hydraulic-magnetic circuit breaker / protector that combines power switching and accurate, reliable circuit protection in one aesthetically pleasing, “1U” or “1RU” sized package.

Designed for rack mount applications, the IAR/IUR/IER/CUR/CER series allows efficient use of rack space without sacrificing performance via proven hydraulic-magnetic technology that provides consistent operation from -40°C to 85°C, with a circuit interrupt capacity up to 5,000 AIC at 80VDC and 2,000 AIC at 250VAC. Available in series trip and mid-trip configurations, with auxiliary alarm switch options to provide monitoring of critical circuits.

The CER series circuit breaker provides the necessary ratings for wireless and wired applications while meeting UL489A and TÜV requirements for approval.



Features

- UL1077, TÜV, UL489A approved
- Designed to fit in a “1RU” application
- 5000 AIC (80VDC), 2000 AIC (250VAC) interrupt capacity
- Series or mid-trip with auxiliary switch alarm options
- Various delays including motor start
- 1 to 2 poles, multiple termination options



POLES & TERMINALS


The Airpax™ IAR/IUR/IER/CUR/CER series is available with one or two poles with various bullet, stud and screw terminals. Engineered for safe, sure operation, the toggle handles may be specified in blue, white, red, orange, green, yellow or black.




DIMENSIONS

Tolerance, unless otherwise noted:
All dimensions are in millimeters [inches]

Single Pole




Two Pole (with or without two handles)




Auxiliary switch wires not shown for clarity


Panel Mounting Detail, Single Pole




Panel Mounting Detail, Two Pole, One Handle





Panel Mounting Detail, Two Pole, Two Handles



Single Pole




Two Pole (with or without 2nd handle)




Bullet Type	Dim. "A"	Dim. "B"	Dim. "C"	Stud Type	Dim. "E"	Dim. "F"
1/4" Bullet	4.778 [121.35]	5.019 [127.48]	∅ 0.251 ± 0.001 ∅ [6.38 ± 0.03]	10-32	0.545 [13.84]	0.622 [15.81]
5/16" Bullet	4.851 [123.22]	5.092 [129.35]	∅ 0.312 ± 0.001 ∅ [7.92 ± 0.03]	M5	0.510 [12.95]	0.588 [14.92]


Single Pole Bullet Terminal Mounting Detail




Two Pole Bullet Terminal Mounting Detail




1/4" Bullet Terminals




5/16" Bullet Terminals



10-32 or M5 Screw Terminals



10-32 or M5 Stud Terminals




CONFIGURATIONS


Series Trip

The most popular configuration for magnetic protectors is the series trip where the sensing coil and the contacts are in series with the load being protected. In addition to providing conventional overcurrent protection, it is simultaneously used as an on-off switch.

Single Pole, Series Trip




Two Pole, Series Trip




Mid-Trip

This is furnished as an integral part of a series pole in single or, multi-pole assemblies. Isolated electrically from the protector's circuit, the switch works in unison with the power contacts and provides indication at a remote location of the protector's ON-OFF status.

Mid-Trip



Breaker shown in ON position or manually turned OFF position




Breaker shown in mid-trip position (electrically tripped)








Auxiliary Switch

This is furnished as an integral part of a series pole in single or, multi-pole assemblies. Isolated electrically from the protector's circuit, the switch works in unison with the power contacts and provides indication at a remote location of the protector's ON-OFF status.

Auxiliary Switch



Breaker shown in OFF position





DELAY CURVES & SPECIFICATIONS

DC, 50/60Hz Delay Curves (typ)

A choice of delays is offered for DC and 50/60Hz applications. Delays 59 and 69 provide fast-acting, instantaneous trip and are often used to protect sensitive electronic equipment (not recommended where known inrush exists). Delays 51 and 61 have a short delay for general purpose applications. Delays 52 and 62 are long enough to start certain types of motors and most transformer and capacitor loads.

Trip Free

Will trip open on overload, even when forcibly held on. This prevents operator from damaging the circuit by holding handle in the ON position.

Trip Indication

The operating handle moves forcibly and positively to the OFF position on overload.

Ambient Operation

Operates normally in temperatures between -40°C and $+85^{\circ}\text{C}$.

Insulation Resistance

Not less than 100 megaohms at 500Vdc.

Dielectric Strength

Shall withstand AC voltage 60 Hz, for 60 seconds between all electrically isolated terminals as described below

Series, switch only: 3,750 VAC

Auxiliary switches: 600 VAC

Series w/ auxiliary switch: 3,750 between main circuit breaker terminal and auxiliary switch terminal.

Shock

Shall not trip when tested per MIL-STD-202, method 213, test condition 1 with 100% rated current applied to delayed units, except 90% current in plane 4, (i.e. handle down). Instantaneous units shall have 80% rated current applied in all planes.

Vibration

Shall not trip when vibrated per MIL-STD-202, method 204, test condition A with 100% rated current applied to delayed units and 80% rated current to instantaneous units.

Endurance

In many applications contact wear due to the electrical load determines unit life. At maximum electrical ratings, the IAR/UR/IER/CUR/CER can perform 10,000 operations at rated current and voltage at a maximum rate of 6 operations per minute.



OPERATING CHARACTERISTICS

Inrush Pulse Tolerance

Many circuit protector applications involve a transformer turn-on, an incandescent lamp load, or a capacitor charge from a DC source. Each of these applications has one common factor: a steep transient of very high current amplitude and short duration. This takes the form of a spike or a single pulse and is the cause of most nuisance tripping associated with magnetic circuit breakers.

The IAR/IUR/IER/CUR/CER series will withstand, without tripping, a single pulse of 8 milliseconds duration (half sine wave configuration) and peak amplitude of 10 times its rating.

MAXIMUM DCR AND IMPEDANCE (APPROXIMATE VALUES)

Current Ratings (Amps)	DC Resistance (Ohms) 51, 52, 53, 59	50/60Hz Impedance (Ohms) 61, 62, 63, 69
2.0	0.027	0.038
3.0	0.074	0.098
5.0	0.037	0.048
7.5	0.025	0.029
15.0	0.010	0.011
32.0	0.003	0.003
40.0	0.003	0.003
50.0	0.0024	0.0025
65.0	0.0021	—

Tolerance: 2 to 2.5 amps $\pm 20\%$; 2.6 to 20 amps $\pm 25\%$; 21 to 50 amps $\pm 50\%$

*Consult factory for special values and for coil impedance of delays not shown

Auxiliary Switch Rating		
10.0 amps	@	250 VAC, 60 Hz
3.0 amps	@	50 VDC
1.0 amps	@	80 VDC

Approximate Weight Per Pole	
1 pole	134 grams
2 pole	263 grams


Pulse Tolerance	
Delay	134 grams
2 pole	263 grams

Percentage of Rated Current vs Trip Time in Seconds at +25°C (Approximate Values)								
Delay	100%	125%	150%	200%	400%	600%	800%	1000%
51	No Trip	0.5 to 6.5	0.3 to 3	0.1 to 1.2	0.031 to 0.5	0.011 to 0.25	0.004 to 0.1	0.004 to 0.08
52	No Trip	2 to 60	1.8 to 30	1 to 10	0.15 to 2	0.015 to 1	0.008 to 0.5	0.006 to 0.1
59	No Trip	0.120 max	0.1 max	0.05 max	0.022 max	0.017 max	0.017 max	0.017 max
61	No Trip	0.7 to 12	0.35 to 7	0.13 to 3	0.03 to 1	0.015 to 0.3	0.01 to 0.15	0.008 to 0.1
62	No Trip	10 to 120	6 to 60	2 to 20	0.2 to 3	0.015 to 2	0.015 to 0.8	0.01 to 0.25
63	No Trip	50 to 700	30 to 400	10 to 150	1.5 to 20	0.015 to 10	0.013 to 0.85	0.013 to 0.5
69	No Trip	0.12 max	0.1 max	0.05 max	0.022 max	0.017 max	0.017 max	0.017 max

HARDWARE


Handle Lock

A handle lock option is available to prevent accidental actuation of the handle. The handle lock may be used in the ON or OFF position. Use of the handle lock on breakers with alarm style auxiliary switches may defeat the alarm feature on electrical trip. This option is available separately or pre-assembled (on single pole constructions only).




Mid-Trip

The handle position indicates the status of the circuit breaker. In addition to full ON and full OFF positions, there is a middle "MID-TRIP" position indicating that the breaker has electrically tripped from an overload. It is available in single pole and multi-pole (handle per pole only) series constructions. Switch only configuration is not available in mid-trip build. An auxiliary switch can be furnished as an integral part of the mid-trip breaker. The switch provides an indication at a remote location when the circuit breaker has electrically tripped and handle is in the mid-trip position.




Barrier (-B)




Bullets


Socket 1/4-20 UNC-2A
Order # 641-480-5032
(silver plated copper)



Socket 1/4-20 UNC-2A
Order # 641-480-5030
(silver plated copper)



Socket 1/4-20 UNC-2A
Order # 641-480-5022
(silver plated copper)



Nut 1/4-20 UNC-2B
Order # 388-899-5010
(silver plated copper)



ORDERING OPTIONS

Example : IER1-1REC4C-52-20.0-AD-01-T

The ordering code for these circuit breakers / protectors may be determined by following the steps in the decision tables shown here. The example shown is the code for a UL1077 & TÜV approved circuit protector with series trip, one handle per unit, single pole circuit protector with 10-32 terminal screws standard and a mechanical auxiliary switch. This unit is designed with a slow DC time delay and a rating of 20 amperes with optional metric threads and optional 80VDC capability. Handle color is black with white markings, and it has met all the selection criteria to obtain the TÜV approval.

To determine the ordering code for your particular unit, simply follow the steps shown, then fill in the letters and/or numbers in the boxes. Space is available on the circuit breaker label for your part number (up to 12 digits). You may then use your own part number to place an order or as a reference for further questions you may have. This option does require a factory assigned part number for traceability to your drawing or internal part number.

IER 1 1REC4C - 52 - 20.0 - AD - 01 - T

Type

IAR: Magnetic circuit protector, one handle per unit
IARH: Magnetic circuit protector, one handle per pole
IER: UL1077 & TÜV, series trip, one handle per unit
IERH: UL1077 & TÜV, series trip, one handle per pole
IUR: UL1077, series trip, one handle per unit
IURH: UL1077, series trip, one handle per pole
IMR: UL1077 & TÜV, mid trip, one handle per unit
IMRH: UL1077 & TÜV, mid trip, one handle per pole
CER: UL489A & TÜV, series trip, one handle per unit
CERH: UL489A & TÜV, series trip, one handle per pole
CUR: UL489A, series trip, one handle per unit
CURH: UL489A, series trip, one handle per pole
CMR: UL489A & TÜV, mid trip, one handle per unit
CMRH: UL489A & TÜV, mid trip, one handle per pole

Terminal
 10-32 screw terminal, standard (no entry)
K: 10-32 stud terminal
B: 0.250" bullet terminal

The shaded areas denote TÜV approval options.
 This approval requires the addition of a "T" at the end of the part number (8th decision).
 The "T" will automatically be added to any part number formed entirely from these shaded decisions. If non-shaded areas are selected, the unit will not be TÜV approved, but other approvals (if applicable) will still apply

Number of Poles

1: Single pole
11: Two pole

Internal Configuration

-1: Series trip
-1REC4C: Mechanical trip auxiliary switch*
-1RS4C: Electrical trip auxiliary switch*
-1RLS4C: Electrical trip auxiliary switch* (mid-trip only)
-1REG4C: Series trip with auxiliary switch* 0.110 quick-connects (gold contacts)
-1REC40: Mechanical trip auxiliary switch**
-1RS40: Electrical trip auxiliary switch*
-1RLS40: Electrical trip auxiliary switch* (mid-trip only)
-1REG40: Series trip with auxiliary switch*
 0.110 quick-connects (gold contacts) *Alarms when circuit breaker closes
 **Alarms when circuit breaker opens

Only one auxiliary switch is normally supplied on two pole units. Switch is located in the right hand pole (viewed from terminal end) unless otherwise specified.

Frequency & Delay

-51: DC short delay
-52: DC long delay
-59: DC 125% instant trip
-61: 50 - 60 Hz short delay
-62: 50 - 60 Hz Long Delay
-63: 50 - 60 Hz motor start / extra long delay (30A max)
-69: 50 - 60 Hz 125% instant trip

Rated Current

Use three numbers to print required current value between 2.00 amps minimum and 50.0 amps maximum.

Optional

-A: Metric thread mounting (M3) & terminals (M5)
-B: Barrier (AC only)
-C: 65 VDC
-D: 80VDC
-E: 0.312" diameter bullet (standard is 0.250" when prex with "B" is chosen in rst decision)
-F: 250VAC
-L: Handle Lock

Notes:
 1. One or more descriptions may be used as required (for example, to get a barrier, 250VAC and handle lock, put -BFL)
 2. When the sixth decision is not required, the seventh decision may be substituted and U.S. thread will be supplied

Handle Color & Markings

-00: Black	-01: Black w/ white markings (standard)
-10: Yellow	-11: Yellow w/ black markings
-20: Red	-21: Red w/ white markings
-30: Blue	-31: Blue w/ white markings
-40: Green	-41: Green w / white markings
-60: Orange	-61: Orange w/ black markings
-90: White	-91: White w/ black markings

TÜV Approval

Per first decision's description: The shaded areas denote TÜV approval options. This approval requires the addition of a "T" at the end of the part number (8th decision).



AGENCY APPROVALS & CERTIFICATIONS

Ratings	Voltage	A.I.C.	Agency Approvals	Poles
2 to 65 amps	80VDC	5,000	UL489A, TÜV EN60947-2 & C-UL	1
2 to 50 amps	80VDC	5,000	UL1077, TÜV EN60943 & C-UL	2
2 to 50 amps	250VAC	2,000	UL1077, TÜV EN60943 & C-UL	2



WARNINGS



RISK OF MATERIAL DAMAGE AND HOT ENCLOSURE

- The product's side panels may be hot, allow the product to cool before touching
- Follow proper mounting instructions including torque values
- Do not allow liquids or foreign objects to enter this product

Failure to follow these instructions can result in serious injury, or equipment damage.



HAZARD OF ELECTRIC SHOCK, EXPLOSION OR ARC FLASH

- Disconnect all power before installing or working with this equipment
- Verify all connections and replace all covers before turning on power

Failure to follow these instructions can result in death or serious injury

Sensata Technologies, Inc. ("Sensata") data sheets are solely intended to assist designers ("Buyers") who are developing systems that incorporate Sensata products (also referred to herein as "components"). Buyer understands and agrees that Buyer remains responsible for using its independent analysis, evaluation and judgment in designing Buyer's systems and products. Sensata data sheets have been created using standard laboratory conditions and engineering practices. Sensata has not conducted any testing other than that specifically described in the published documentation for a particular data sheet. Sensata may make corrections, enhancements, improvements and other changes to its data sheets or components without notice.

Buyers are authorized to use Sensata data sheets with the Sensata component(s) identified in each particular data sheet. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER SENSATA INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY THIRD PARTY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT, IS GRANTED HEREIN. SENSATA DATA SHEETS ARE PROVIDED "AS IS". SENSATA MAKES NO WARRANTIES OR REPRESENTATIONS WITH REGARD TO THE DATA SHEETS OR USE OF THE DATA SHEETS, EXPRESS, IMPLIED OR STATUTORY, INCLUDING ACCURACY OR COMPLETENESS. SENSATA DISCLAIMS ANY WARRANTY OF TITLE AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, QUIET ENJOYMENT, QUIET POSSESSION, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS WITH REGARD TO SENSATA DATA SHEETS OR USE THEREOF.

All products are sold subject to Sensata's terms and conditions of sale supplied at www.sensata.com SENSATA ASSUMES NO LIABILITY FOR APPLICATIONS ASSISTANCE OR THE DESIGN OF BUYERS' PRODUCTS. BUYER ACKNOWLEDGES AND AGREES THAT IT IS SOLELY RESPONSIBLE FOR COMPLIANCE WITH ALL LEGAL, REGULATORY AND SAFETY-RELATED REQUIREMENTS CONCERNING ITS PRODUCTS, AND ANY USE OF SENSATA COMPONENTS IN ITS APPLICATIONS, NOTWITHSTANDING ANY APPLICATIONS-RELATED INFORMATION OR SUPPORT THAT MAY BE PROVIDED BY SENSATA.

Mailing Address: Sensata Technologies, Inc., 529 Pleasant Street, Attleboro, MA 02703, USA.

CONTACT US

Americas

508-236-2551
electrical-protection-sales@
sensata.com

Europe, Middle East & Africa

+31743578156
info-sse@list.sensata.com

Asia Pacific

sales.isasia@list.sensata.com
China +86 (21) 2306 1500
Japan +81 (45) 277 7117
Korea +82 (31) 601 2004
India +91 (80) 67920890
Rest of Asia +886 (2) 27602006
ext 2808